



60 Hz

Especificación del grupo electrógeno 220/127V 60HZ				Especificación del motor			Ficha de datos
Modelo de grupo electrógeno	KVA		Contras 100% (L/h)	Modelo de motor	Cilindro	Gobernador	
	ESP	PPR					
G11P	11	10	3	403D-11G	3L	MEC	1,131
G16P	16	15	4,4	403D-15G	3L	MEC	1,496
G25P	25	22,5	6,2	404D-22G	4L	MEC	2,216
G35P	35	32,5	8,3	404D-22TG	4L	MEC	2,216
G38.5P	38,5	35	8,9	404D-22TAG	4L	MEC	2,216
G38.5P	38,5	35	8,6	1103A-33G	3L	MEC	3,3
G45P	45	41	12,9	1103A-33TG1	3L	MEC	3,3
G50P	50	45	12,9	1103A-33TG1	3L	MEC	3,3
G57.5P	57,5	52,5	12,9	1103A-33TG1	3L	MEC	3,3
G75P	75	67,5	16,6	1103A-33TG2	3L	MEC	3,3
G69P	68,8	62,5	9	1104D-44TG1	4L	N / A	4,4
G82.5P	82,5	75	17,8	1104A-44TG1	4L	N / A	4,4
G80P	80	72,5	23,13	1104D-E44TG1	4L	N / A	4,4
G100P	100	90	22,3	1104A-44TG2	4L	Electrónico	4,4
G100P	100	90	17,8	1104D-E44TAG1	4L	N / A	4,4
G100P	100	90	22	1104C-44TAG1	4L	N / A	4,4
G125P	125	115	26,9	1104C-44TAG2	4L	Electrónico	4,4
G125P	125	115	27,65	1104D-E44TAG2	4L	Electrónico	4,399
G150P	150	138	35,2	1106A-70TG1	6L	Electrónico	7,01
G165P	165	150	35,2	1106A-70TG1	6L	Electrónico	7,01
G185P	185	168	45,8	1106A-70TAG2	6L	Electrónico	7,01
G185P	185	168	39,7	1106D-E70TAG2	6L	Electrónico	7,01
G195P	195	175	42,3	1106D-E70TAG3	6L	Electrónico	7,01
G210P	210	190	41,6	1106A-70TAG3	6L	MEC	7,01
G250P	250	225	48	1106D-E70TAG4	6L	Electrónico	7,01
G235P	235	215	44,6	1506A-E88TAG1	6L	Electrónico	8,8
G270P	270	245	44,6	1506A-E88TAG1	6L	Electrónico	8,8
G300P	300	275	63,1	1506A-E88TAG3	6L	Electrónico	8,8
G315P	315	288	63,1	1506A-E88TAG3	6L	Electrónico	8,8
G344P	344	313	68,2	1506A-E88TAG4	6L	Electrónico	8,8
G385P	385	350	77,1	1506A-E88TAG5	6L	Electrónico	8,8
G440P	440	400	84	2206C-E13TAG2	6L	ECU	12,5
G440P	440	400	87	2206D-E13TAG2	6L	ECU	12,5
G500P	500	450	84	2206C-E13TAG3	6L	ECU	12,5
G440P	440	400	83	2206A-E13TAG5	6L	Electrónico	12,5
G500P	500	450	91	2206A-E13TAG6	6L	ECU	12,5
G560P	560	510	113	2506D-E15TAG1	6L	ECU	15,2
G560P	560	510	100	2506C-E15TAG1	6L	ECU	15,2
G633P	633	575	121	2506C-E15TAG3	6L	ECU	15,2
G700P	700	638	135	2506C-E15TAG4	6L	ECU	15,2
G575P	575	525	101	2506A-E15TAG3	6L	Electrónico	15,2
G633P	633	575	115	2506A-E15TAG4	6L	Electrónico	15,2
G688P	688	625	127	2806A-E18TAG1A	6L	Electrónico	18,13
G770P	770	700	144	2806A-E18TAG3	6L	Electrónico	18,13
G770P	770	700	145	2806C-E18TAG3	6L	ECU	18,13

  

Especificación del grupo electrógeno 440/254V 60HZ				Especificación del motor			Ficha de datos
Modelo de grupo electrógeno	KVA		Contras 100% (L/h)	Modelo de motor	Cilindro	Gobernador	
	ESP	PPR					
G825P	825	750	177	4006-23TAG2A	6L	Electrónico	22,921
G910P	910	825	200	4006-23TAG3A	6L	Electrónico	22,921
G963P	963	875	201	4008TAG1	8L	Electrónico	30,561
G1100P	1100	1000	213	4008-TAG2	8L	Electrónico	30,561
G1375P	1375	1250	260	4012-46TWG2A	12V	Electrónico	45,842
G1500P	1500	1375	281	4012-46TWG3A	12V	Electrónico	45,842
G1650P	1650	1500	323	4012-46TWG4A	12V	Electrónico	45,842
G1650P	1650	1500	315	4012-46TAG2A	12V	Electrónico	45,842
G1875P	1875	1700	356	4012-46TAG3A	12V	Electrónico	45,842